

## NCK-N-6-2

### N Connectors, DC~6GHz, Economic Type

Features:  
\* High Precision

Applications:  
\* Calibration  
\* Laboratory Test



#### Description

With the components in these kits you can make error-corrected measurements of devices supplied with N connectors from DC to 6 GHz.

#### Components

Part Number	Description	Frequency	Impedance	VSWR	Phase Accuracy	Inner Conductor	Outer Conductor	Size			
		(GHz)	(Ω)	(Max.)	(°, Max.)			(mm)			
NONC-M-6-2	N male open	DC~6	50	-	±1	Without inner conductor	Passivated stainless steel	-			
NONC-F-6-2	N female open					Gold plated beryllium copper		-			
NSNC-M-6-2	N male short			-	±1	Passivated stainless steel		-			
NSNC-F-6-2	N female short					Gold plated beryllium			-		
NCT-N-C-M-6-2	N male termination			1.035	-	Gold plated beryllium		-			
NCT-N-C-F-6-2	N female termination					m copper			-		
NW-N1-CK	N torque wrench			-	-	Nickel plated tool steel (Head)		Aluminium, anodised (Handle)		19.1 (Opening size)	
NANNC-MM-2*	N male to N male adapter			1.05	-	-		-	Gold plated beryllium copper	Passivated stainless steel	-
NANNC-MF-2*	N male to N female adapter										
NANNC-FF-2*	N female to N female adapter										
Storage Box		-	-	-	-	Wood		275*200*80/ 145*145*60			

“\*” Equal phase adapter

#### How To Order

**NCK-N-6-2-10** All the 10 components in one box.



TOMORROW DISCOVERED

## Calibration Kits

- NCK-N-6-2-3M** Three in one box, including open, short and termination, male, NONC-M-6-2, NSNC-M-6-2, NCT-N-C-M-6-2.
- NCK-N-6-2-3F** Three in one box, including open, short and termination, female, NONC-F-6-2, NSNC-F-6-2, NCT-N-C-F-6-2.
- NCK-N-6-2-6** Six in one box, including NCK-N-6-2-3M and NCK-N-6-2-3F.

To order a single component, specify the npart umber in the first column.