

# NA750

## Ultra Low Loss & Phase Stable

- |   |   |
|---|---|
| <b>Features:</b><br>* Low Insertion Loss<br>* High Phase Stability<br>* High Power<br>* Low PIM | <b>Applications:</b><br>* Phased-array Radar<br>* Satellite Communication<br>* Avionics |
|---|---|

### Electrical

Frequency:	DC~18GHz
Cut-off Frequency:	20GHz
Impedance:	50Ω
Velocity of Propagation:	83%
Shielding Effectiveness:	90dB min.
Voltage Withstand:	2500VC
PIM:	-155dBc
Phase Stability:	750PPM@-55°C~+85°C max.


### Mechanical

Bend Radius (installation):	37.0mm
Bend Radius (repeated):	74.0mm
Weight:	125g/m

### Environmental

Temperature: -55~+165°C

### Construction



No.	Name	Size (mm)	Material
1	Inner Conductor	2.10	Silver-plated copper
2	Dielectric	5.70	Low density PTFE
3	Inner Shield	5.95	Silver-plated copper tape
4	Outer Shield	6.60	Silver-plated copper braid
5	Jacket	7.40	PFA

### Attenuation & Power Handling

Frequency (GHz)	0.1	0.3	0.5	1	3	6	10	12.4	18
Attenuation*1 (dB/100m)	5.0	8.6	11.2	15.8	27.5	39.1	50.7	56.6	68.5
Average Power*2 (W)	5526	3186	2465	1740	1000	704	542	486	401

[1] VSWR:1.0; Ambient: +25°C (77°F)

[2] VSWR:1.0; Ambient: +40°C (104°F); Sea level

Calculate Cable Attenuation: Attenuation (dB/100m) = 0.496490 \* √F (MHz) + 0.000104 \* F (MHz)

Calculate Connector Attenuation: Attenuation (dB) = 0.03 \* √F (GHz)

### How To Order

#### NA750-X-Y-Z

- X: Frequency in GHz  
 Y: Connector type  
 Z: Length in meters

#### Examples:

To order a NA750 cable assembly, DC-18GHz, N male to SMA female, 0.5 meter, specify NA750-18-SFN-0.5.

#### Connector naming rules:

- S - SMA (18GHz, VSWR 1.25)
- N - N (18GHz, VSWR 1.25)
- T - TNC (18GHz, VSWR 1.25)

Female Connector - Add 'F' after connector name

Right Angle - Add 'R' after connector name (VSWR increase 0.1)