

NCK-J-18

7mm Connectors, DC~18GHz

Features:
* High Precision

Applications:
* Calibration
* Laboratory Test



Description

With the components in these kits you can make error-corrected measurements of devices supplied with 7mm connectors from DC to 18 GHz.

Components

Part Number	Description	Frequency	Impedance	VSWR	Phase Accuracy	Inner Conductor	Outer Conductor	Size
		(GHz)	(Ω)	(Max.)	(°, Max.)			(mm)
NOJC-18	7mm open	DC~18	50	-	±1	Gold plated beryllium copper	Gold plated beryllium copper	-
NSJC-18	7mm short			-	±1			-
NCTJ-C-18	7mm termination			1.048	-			-
NWJ1-CK	7mm torque wrench			-	-	Nickel plated tool steel (Head)	Aluminium, anodised (Handle)	19.1mm (Opening size)
NANJC-M*	N male to 7mm adapter			1.06	-	Gold plated beryllium copper	Passivated stainless steel	-
NANJC-F*	N female to 7mm adapter							
Storage Box				-	-	-	-	Wood

* Equal phase adapter

How To Orders

NCK-J-18-6 All the 6 components in one box.

To order a single component, specify the part number in the first column.